

QUICK SPECS

Compaq S910 Monitors

MODELS

S910 Color¹ Monitor
 Model PE1132
 138485-001

SPECIFICATIONS

S910 Color¹ Monitor

| | | | |
|--|--|--------------------------------------|-----------------------------------|
| Type | Color multiple scan with Invar Shadow Mask | | |
| Picture Tube (diagonal) | 19 in Flat Square | | |
| Viewable (diagonal) | 18 in (45.7 cm) | | |
| Horizontal Dot Pitch | 0.23 mm | | |
| Trio Dot Pitch | 0.26 mm | | |
| Max Refresh/ Preset Graphic Modes² | 1600 x 1200 75 Hz/60 and 75 Hz | 1280 x 1024 89 Hz/75 and 85 Hz | 1024 x 768 118 Hz/75 and 85 Hz |
| | 800 x 600 152 Hz/75 and 85 Hz | 640 x 480 160 Hz/60, 75 and 85 Hz | 640 x 350 160 Hz |
| Text Mode | 720 x 400 85 Hz | | |
| Mac Compatible Modes³ | 832 x 624 75 Hz | 1152 x 870 75 Hz | |
| User-Programmable/ Preset Graphic Modes | 4/14 | | |
| Anti-Glare/Anti-Static | Yes/No | | |
| Plug and Play | Yes | | |
| Agency Approvals/Certifications | | | |
| UL Approval | Yes | | |
| ISO9241-3 VOT Guidelines Approval | Yes | | |
| MPR-II Compliant | Yes | | |
| FCC Approval | Yes | | |
| Energy Star Compliant | Yes | | |
| TCO 99 Compliant | Only EMEA, APD, CKK versions | | |
| Tilt Base (up/down) | 15°/5° | | |
| Swivel | ±45° either side of center | | |
| On-Screen Controls | Yes | | |
| Language Selection | | | |
| English | Yes | | |
| German | Yes | | |
| French | Yes | | |
| Spanish | Yes | | |
| Italian | Yes | | |
| Dutch | Yes | | |
| User Controls | | | |
| Brightness, Contrast | Yes | | |
| Size and Positioning | Yes | | |
| Pincushion (barrel) | Yes | | |
| Trapezoid | Yes | | |
| Tilt (rotation) | Yes | | |
| Color temperature | Yes | | |
| Parallelogram | Yes | | |
| Pincushion Balance | Yes | | |
| Individual Color Control | Yes | | |
| Moiré Cancellation | Yes | | |
| Convergence | No | | |
| Overscan | No | | |
| Serial Number Display | No | | |
| Power Saver on/off | No | | |
| Display Mode | Yes | | |
| Degauss | Yes | | |
| Factory Reset | Yes | | |
| Intelligent Manageability | | | |
| AssetControl ⁴ | Yes | | |
| USB Capabilities | With Optional USB Hub (138638-001) | | |



SPECIFICATIONS *(continued)*

S910 Color¹ Monitor *(continued)*

| | |
|---|--|
| Pixel Clock Speed | 202.5 MHz |
| Input Impedance | 75 Ohms |
| Horizontal Frequency | 30 to 95 kHz |
| Vertical Frequency | 50 to 160 Hz |
| Power Supply ALS | 90 to 127 & 195 to 265 VAC; 47.5 to 63 Hz Universal Auto-Sensing |
| Maximum Power Rating | 130 Watts |
| Power Consumption (Suspend/Sleep) | < 10W/< 5W |
| Synch Input | TTL separate synch |
| Signal Cable | 15-pin miniature D-sub |
| Dimensions (H x W x D) | 19.7 x 17.7 x 17.7 in/ 50 x 45 x 45 cm |
| Weight | 43.5 lbs/19.8 kg |
| Operating Humidity (non-condensing) | 20% to 80% |
| Operating Temperature | 10°to 40°C |
| 48-Hour Direct Replacement ⁵ | If for any reason this monitor fails during the parts warranty, Compaq guarantees that a new or like-new monitor replacement will be in the hands of the user within 48 hours. |
| Warranty ⁵ | Three-year; First year, parts, labor, and on-site repair, Second and Third years, parts only |

COMPATIBILITY

Portables

Compaq Armada 7800
Compaq Armada 7400
Compaq Armada 6500
Compaq Armada 3500
Compaq Armada 1750
Compaq Armada 1700
Compaq Armada 1500c

Desktops

Compaq Deskpro EN Series Desktop
Compaq Deskpro EN Series Minitower
Compaq Deskpro EN Series Small Form Factor
Compaq Deskpro EP Series

COMPATIBILITY *(continued)*

Workstations

Compaq Professional Workstation XP1000
Compaq Professional Workstation AP500

Servers

Compaq ProLiant 7000 Xeon™
Compaq ProLiant 6500 Xeon
Compaq ProLiant 6000 Xeon
Compaq ProLiant 5500 Xeon
Compaq ProLiant 3000 Pentium® III
Compaq ProLiant 3000 6/450
Compaq ProLiant 1600 6/500
Compaq ProLiant 1600 (100 MHz)
Compaq ProLiant 800 (500 MHz)
Compaq ProSignia 720

¹ AssetControl monitor. AssetControl features are accessible with Compaq desktops featuring Intelligent Manageability.

² All modes are non-interlaced unless specified otherwise.

³ Adapter required.

⁴ When used with Compaq Intelligent Manageability CPUs and appropriate network software.

⁵ Certain restrictions and exclusions apply. Consult the Compaq Customer Service Support Center for details. In Canada, consult the Product Information Center at 1-800-567-1616 for details.

Compaq, registered trademarks of Compaq Computer Corporation.

Other product names mentioned herein may be trademarks and/or registered trademarks of their respective companies.

©1999 Compaq Computer Corporation. All rights reserved. The information in this publication is subject to change without notice. Printed in Canada.